

SIMATIC ET 200SP, ANALOG INPUT MODULE, AI ENERGY METER 400V AC ST, FITS TO BU-TYPE D0, CHANNEL DIAGNOSIS



| General information                                      |   |
|--|---|
| Product type designation                                 | ET 200SP, AI Energy Meter 400 V AC ST, PU 1 |
| Firmware version   | V3.0  |
| usable BaseUnits   | BU type D0, BU20-P12+A0+0B                  |
| Product function   |   |
| • Voltage measurement                                    | Yes   |
| • Voltage measurement with voltage transformers          | No  |
| • Current measurement                                    | Yes   |
| • Phase current measurement without current transformers | No  |
| • Phase current measurement with current transformers    | Yes   |
| • Energy measurement                                     | Yes   |
| • Frequency measurement                                  | Yes   |
| • Power measurement                                      | Yes   |
| • Active power measurement                               | Yes   |
| • Reactive power measurement                             | Yes   |
| • I&M data   | Yes; I&M0 to I&M3                           |

|   |   |
|---|---|
| • Isochronous mode  | No  |
| <b>Engineering with</b>                                   |   |
| • STEP 7 TIA Portal configurable/integrated as of version | V13 SP1                                   |
| • STEP 7 configurable/integrated as of version            | V5.5 SP4 and higher                       |
| • PROFIBUS as of GSD version/GSD revision                 | GSD Revision 5                            |
| • PROFINET as of GSD version/GSD revision                 | V2.3                                      |
| <b>Operating mode</b>                                     |   |
| • cyclic measurement                                      | Yes                                       |
| • acyclic measurement                                     | Yes                                       |
| • Acyclic measured value access                           | Yes                                       |
| • Fixed measured value sets                               | Yes                                       |
| • Freely definable measured value sets                    | No  |
| <b>Configuration control</b>                              |   |
| via dataset   | Yes                                       |
| <b>CiR – Configuration in RUN</b>                         |   |
| Reparameterization possible in RUN                        | Yes                                       |
| Calibration possible in RUN                               | No  |
| <b>Installation type/mounting</b>                         |   |
| Mounting position   | Any                                       |
| <b>Supply voltage</b>                                     |   |
| Design of the power supply                                | Supply via voltage measurement channel L1 |
| Type of supply voltage                                    | 100 - 240 V AC                            |
| permissible range, lower limit (AC)                       | 90 V                                      |
| permissible range, upper limit (AC)                       | 264 V                                     |
| <b>Line frequency</b>                                     |   |
| • permissible range, lower limit                          | 47 Hz                                     |
| • permissible range, upper limit                          | 63 Hz                                     |
| <b>Power loss</b>   |   |
| Power loss, typ.  | 0.6 W                                     |
| <b>Address area</b>                                       |   |
| Address space per module                                  |   |
| • Address space per module, max.                          | 44 byte; 32 byte input / 12 byte output   |
| <b>Hardware configuration</b>                             |   |
| Automatic encoding  |   |
| • Mechanical coding element                               | Yes                                       |
| <b>Time of day</b>  |   |
| Operating hours counter                                   |   |
| • present   | No  |

## Analog inputs

|                                 |   |
|---------------------------------|---|
| Cycle time (all channels), typ. | 50 ms; Time for consistent update of all measured and calculated values (cyclic und acyclic data) |
|---------------------------------|---|

## Interrupts/diagnostics/status information

### Alarms

|                      |     |
|----------------------|-----|
| • Diagnostic alarm   | Yes |
| • Limit value alarm  | No  |
| • Hardware interrupt | No  |

### Diagnostics indication LED

|  |                         |
|--|-------------------------|
| • Monitoring of the supply voltage (PWR-LED) | Yes                     |
| • Channel status display                     | Yes; Green LED          |
| • for channel diagnostics                    | Yes; red Fn LED         |
| • for module diagnostics                     | Yes; green/red DIAG LED |

## Integrated Functions

### Measuring functions

|   |  |
|---|--|
| • Measuring procedure for voltage measurement | TRMS                                     |
| • Measuring procedure for current measurement | TRMS                                     |
| • Type of measured value acquisition          | seamless                                 |
| • Curve shape of voltage                      | Sinusoidal or distorted                  |
| • Buffering of measured variables             | No                                       |
| • Parameter length                            | 38 byte                                  |
| • Bandwidth of measured value acquisition     | 2 kHz; Harmonics: 39 / 50 Hz, 32 / 60 Hz |

### Operating mode for measured value acquisition

|   |                     |
|---|---------------------|
| — automatic detection of line frequency | No; Parameterizable |
|---|---------------------|

### Measuring range

|                               |       |
|-------------------------------|-------|
| — Frequency measurement, min. | 45 Hz |
| — Frequency measurement, max. | 65 Hz |

### Measuring inputs for voltage

|   |       |
|---|-------|
| — Measurable line voltage between phase and neutral conductor       | 230 V |
| — Measurable line voltage between the line conductors               | 400 V |
| — Measurable line voltage between phase and neutral conductor, min. | 90 V  |
| — Measurable line voltage between phase and neutral conductor, max. | 264 V |
| — Measurable line voltage between the line conductors, min.         | 155 V |
| — Measurable line voltage between the line conductors, max.         | 460 V |

|   |  |
|---|--|
| — Measurement category for voltage measurement in accordance with IEC 61010-2-030 | CAT II; CAT III in case of guaranteed protection level of 1.5 kV |
| — Internal resistance line conductor and neutral conductor                        | 3.4 MΩ   |
| — Power consumption per phase   | 20 mW  |
| — Impulse voltage resistance 1,2/50μs   | 1 kV   |

#### Measuring inputs for current

|  |  |
|--|--|
| — measurable relative current (AC), min.                       | 5 %; Relative to the secondary rated current; 1 A, 5 A   |
| — measurable relative current (AC), max.                       | 100 %; Relative to the secondary rated current; 1 A, 5 A |
| — Continuous current with AC, maximum permissible              | 5 A  |
| — Apparent power consumption per phase for measuring range 5 A | 0.6 V·A  |
| — Rated value short-time withstand current restricted to 1 s   | 100 A  |
| — Input resistance measuring range 0 to 5 A                    | 25 mΩ; At the terminal                                   |
| — Zero point suppression                                       | Parameterizable: 20 - 250 mA, default 50 mA              |
| — Surge strength   | 10 A; for 1 minute                                       |

#### Accuracy class according to IEC 61557-12

|                                     |                                   |
|-------------------------------------|-----------------------------------|
| — Measured variable voltage         | 0.5                               |
| — Measured variable current         | 0.5                               |
| — Measured variable apparent power  | 1                                 |
| — Measured variable active power    | 1                                 |
| — Measured variable reactive power  | 1                                 |
| — Measured variable power factor    | 0.5                               |
| — Measured variable active energy   | 1                                 |
| — Measured variable reactive energy | 2                                 |
| — Measured variable phase angle     | ±1 °; not covered by IEC 61557-12 |
| — Measured variable frequency       | 0.05                              |

#### Potential separation

##### Potential separation channels

- between the channels and backplane bus Yes; 3 700V AC (type test) CAT III

#### Isolation

Isolation tested with 2 300V AC for 1 min. (type test)

#### Ambient conditions

##### Ambient temperature during operation

- horizontal installation, min. 0 °C
- horizontal installation, max. 60 °C
- vertical installation, min. 0 °C
- vertical installation, max. 50 °C

## Dimensions

|        |       |
|--------|-------|
| Width  | 20 mm |
| Height | 73 mm |
| Depth  | 58 mm |

## Weights

|                            |      |
|----------------------------|------|
| Weight (without packaging) | 45 g |
|----------------------------|------|

## Other

### Data for selecting a current transformer

- Burden power current transformer  $\times/1A$ , min. As a function of cable length and cross section, see device manual
- Burden power current transformer  $\times/5A$ , min. As a function of cable length and cross section, see device manual

**last modified:** 01/17/2017